



DSR-4440

Commercial Integrated Receiver/Decoder



A Multi-Format Digital Satellite Receiver for Cable Programmers and Operators

Highlights Include:

- Stackable 1RU chassis design
- 2 RF Inputs (L-Band)
- ASI input
- Multi-format MPEG-2/4 HD/SD processing
- Advanced Modulation support with DVB-S QPSK, and DVB-S2 QPSK/8PSK
- DigiCipher II conditional access control
- Dolby® Digital audio processing
- VBI reinsertion for closed caption
- Quick disconnect terminals for easy installation
- DTMF cue tones for local ad insertion
- Dual ASI and Gig-E transport outputs
- Composite video and dedicated video diagnostics outputs
- 10/100 BaseT Ethernet port for SNMP and web browser monitoring and control




For more information regarding any of these features contact your Motorola sales representative.

The DSR-4440 Integrated Receiver/Decoder from Motorola brings revolutionary technology advances from a recognized leader in satellite program delivery. The DSR-4440 decodes MPEG-2 or MPEG-4 services and delivers outstanding video and audio performance. Its sleek packaging design fits in a standard 19" relay rack and requires only a single rack unit of space.

The Motorola DSR-4440 comes equipped with industry standard output interfaces such as Gig-E and dual ASI outputs that enable seamless connections to headend equipment. With advanced modulation support, the DSR-4440 supports both DVB-S QPSK and DVB-S2 QPSK/8PSK.

TECHNICAL SPECIFICATIONS		Contact Closures	
L-Band Input		Number of Closures: 4 (1 alarm)	
Input Frequency:	950 - 2150 MHz	Type: Form C	
Input Impedance:	75 Ω	Ethernet	
Input Connectors:	Two (2) F-type	Connectors:	Two (2) RJ-45
F-Connector:	16V DC min/450 mA	Formats:	10/100BaseT and 1000BaseT
Port-to-Port Isolation:	40 db (minimum)	ASI Output (2) / Input (1)	
Digital Processing		Format:	Asynchronous serial interface
Modulation Modes:	DVB-S QPSK, DVB-S2 QPSK/8PSK	Transmission:	Data byte and packet
Symbol Rates:	1 to 31.25 Msps	Standard:	CENELEC EN 50083-9
QSPK FEC Rates:	1/2, 3/5, 2/3, 3/4, 4/5, 5/6, 7/8	Connector:	BNC
DVB-S2 FEC Rates:	3/5, 2/3, 3/4, 5/6, 8/9, 9/10	Cue Tones	
Composite Video		Signal Type:	Differential output
Frequency Response (NTSC):	±0.9 dB, 1kHz - 4.2 MHz	Signal Level:	0 dBm, ± 3 dB (600 Ω)/tone
Frequency Response (PAL):	±0.9 dB, 1kHz - 4.8 MHz	Connector:	Quick disconnect terminal
Signal/Noise Ratio:	57 dB (min)	Physical	
Differential Gain:	4.0% p-p (max) (10% to 90% APL)	Width:	18.9" (48cm)
Difference Phase:	1.5 deg. (max)	Depth:	20.5" (52.1cm)
Output Impedance:	75 Ω	Height:	1.65" (4.2cm)
Output Level:	1.0 V p-p ± 10%	Weight:	12 lb (5.5kg) approx
Audio		Power Input:	95-240 VAC, 50-60Hz, 60 W max
Output:	2 stereo pair or 4 mono	Operating Temperature:	0 to 50C
Output Level:	±18.0 dBu, ±1.0 dB into 600 Ω balanced load, adjustable (0 to -18 dB)	Humidity:	95%, relative maximum
Frequency Response:	±1.0 dB, 20 Hz to 20 kHz	Display:	2 line, 40 character LCD
Total Harmonic Distortion:	0.4% or better at 1kHz	Other	
Signal/Noise Ratio:	85 dB or better at 1 kHz RE: + 18 dBu, measured at 20 Hz to 20 kHz	Limited Warranty:	One year
Isolation, L/R:	80 dB at 1 kHz	Compliance:	UL/CE listed/approved, FCC part 15
Impedance:	50 Ω		



MOTOROLA
Motorola, Inc. Home & Networks Mobility
6450 Sequence Drive, San Diego, California 92121 U.S.A.
www.motorola.com/business 858-578-2222

MOTOROLA and the Stylized M Logo are registered in the U.S. Patent and Trademark Office. DigiCipher is a registered trademark of General Instrument Corporation, a wholly-owned subsidiary of Motorola, Inc. Dolby Digital is a registered trademark of Dolby Laboratories; Dolby Digital is manufactured under license from Dolby Laboratories. All other product or service names are the property of their registered owners. © Motorola, Inc. 2010 All rights reserved. Features and functions subject to change without notice. 6056-0210-0K